



Deep Sea Electronics Plc

P130 input expansion module /
549 remote annunciator

Operators manual

Author – Tony Manton

Deep Sea Electronics Plc
Highfield House
Hunmanby Industrial Estate
North Yorkshire
YO14 0PH
ENGLAND
Tel +44 (0) 1723 890099
Fax +44 (0) 1723 893303
Email : sales@deepseapl.com

<<< THIS PAGE INTENTIONALLY BLANK >>>

TABLE OF CONTENTS

Section	Page
1 INTRODUCTION	4
2 CLARIFICATION OF NOTATION USED WITHIN THIS PUBLICATION.	4
3 P130 INPUT EXPANSION MODULE	5
3.1 DESCRIPTION OF OPERATION.....	5
3.1.1 TYPICAL CONNECTION SCHEMATIC :	5
3.2 INPUT CONFIGURATION	6
3.3 PANEL LAYOUT	6
3.4 TERMINAL DESCRIPTION	7
3.4.1 CONNECTOR 1.....	7
3.4.2 CONNECTOR 2.....	7
3.5 130 INPUT EXPANSION SPECIFICATION	8
3.6 TYPICAL WIRING DIAGRAM.....	8
4 549 REMOTE ANNUNCIATOR.....	9
4.1 DESCRIPTION OF OPERATION.....	9
4.1.1 FRONT PANEL LAYOUT	9
4.1.2 REAR PANEL LAYOUT	10
4.2 TERMINAL DESCRIPTION	10
4.2.1 CONNECTOR 1.....	10
4.2.2 TYPICAL CONNECTION SCHEMATICS :	11
4.3 549 REMOTE ANNUNCIATOR SPECIFICATION.....	11
4.4 TYPICAL WIRING DIAGRAM.....	11
5 TYPICAL WIRING DIAGRAM OF P130 WITH P549	12

1 INTRODUCTION

The P130 is used to expand the input capability of the 53xx series of DSE controllers. It provides the controllers with 8 additional digital inputs and 2 additional analogue inputs.

Also provided is support for the DSE Model 549 remote annunciator, used to help system manufacturers meet the requirements of the NFPA110 level 1 specifications (USA).

2 CLARIFICATION OF NOTATION USED WITHIN THIS PUBLICATION.



NOTE:

Highlights an essential element of a procedure to ensure correctness.



CAUTION!:

Indicates a procedure or practice which, if not strictly observed, could result in damage or destruction of equipment.



WARNING!:

Indicates a procedure or practice which could result in injury to personnel or loss of life if not followed correctly.



NFPA110

Deep Sea Electronics Plc owns the copyright to this manual, which cannot be copied, reproduced or disclosed to a third party without prior written permission.


National Fire Protection Authority (USA). NFPA110 covers emergency power systems (EPS) including generating systems. NFPA110 Level 2 is met by most DSE controllers. NFPA Level 1 requires additional remote indication of some control and alarm conditions.

3.2 INPUT CONFIGURATION

Configuration of the expansion inputs is performed by configuring the master controller module. This instructs the controller how to interface with the expansion modules. The input expansion module is not directly configurable.

For further details on module configuration, you are referred to the relevant configuration software manual.

3.3 PANEL LAYOUT



3.4 TERMINAL DESCRIPTION

3.4.1 CONNECTOR 1

PIN No	DESCRIPTION	CABLE SIZE	NOTES
1	Plant supply negative	1.0mm ²	
2	Plant supply positive	1.0mm ²	Recommended fuse 2A anti-surge
3	Digital input expansion 1	0.5mm ²	Requires a contact to plant supply negative.
4	Digital input expansion 2	0.5mm ²	Requires a contact to plant supply negative.
5	Digital input expansion 3	0.5mm ²	Requires a contact to plant supply negative.
6	Digital input expansion 4	0.5mm ²	Requires a contact to plant supply negative.
7	Digital input expansion 5	0.5mm ²	Requires a contact to plant supply negative.
8	Digital input expansion 6	0.5mm ²	Requires a contact to plant supply negative.
9	Digital input expansion 7	0.5mm ²	Requires a contact to plant supply negative.
10	Digital input expansion 8	0.5mm ²	Requires a contact to plant supply negative.
11	Analogue input expansion 1	0.5mm ²	Connect to plant supply negative if unused
12	Analogue input expansion 1 return	0.5mm ²	Connect to plant supply negative if unused
13	Analogue input expansion 2	0.5mm ²	Connect to plant supply negative if unused
14	Analogue input expansion 2 return	0.5mm ²	Connect to plant supply negative if unused

3.4.2 CONNECTOR 2


PIN No	DESCRIPTION	CABLE SIZE	NOTES
A	0V	0.5mm ²	Thinner cable will reduce the maximum allowable cable length
B	A	0.5mm ²	
C	B	0.5mm ²	
D	+12V	0.5mm ²	

! CAUTION!: Connector 2 is only intended for connection to the DSE 549 annunciator. Connection to any other device may cause damage and will invalidate the warranty.

3.5 130 INPUT EXPANSION SPECIFICATION

DC Supply	8.0 to 35 V Continuous.
Cranking Dropouts	Able to survive 0 V for 50 mS, providing supply was at least 10 V before dropout and supply recovers to 5V
Max. Operating Current	150mA at 12V. 81mA at 24V. This maximum current includes connection of the P549 remote annunciator, which is powered by the P130.
Dimensions	171mm x 115mm x 49mm (6¾" x 4½" x 2")
Operating Temperature Range	-30°C to +70°C
IP Rating of P130	IP20
Connector 2 max cable length to 549 remote annunciator	<ul style="list-style-type: none"> • 1000m with cable of 0.5mm² cross section • 500m with cable of 0.2mm² cross section (typical 4 core burglar alarm/telephone wire)

3.6 TYPICAL WIRING DIAGRAM



4 549 REMOTE ANNUNCIATOR

4.1 DESCRIPTION OF OPERATION

The model 549 remote annunciator is intended to help system manufacturers meet the requirements of the NFPA110 level 1 specification by providing indication of the required control/alarm status. A 'spare' channel is provided that be configured to one of a number of choices to help the system manufacturer meet more complex specifications.

The 549 is connected via a 4 core cable to the connector 2 socket of the DSE P130 input expansion module.


For connection details, see the sections headed Terminal Description and Typical Wiring Diagram elsewhere in this manual.

Correct connection of the 4 core cable to a correctly connected and operating P130 input expansion module will illuminate the Power LED.

If the P130 input expansion module does not have DC power connected to it, or the 4 core cable is not correctly terminated, the 549's Power LED will remain extinguished.


Failure of the data signal to the 549 from the P130 (terminals B & C) will cause the Link Lost LED to flash.

The 549 features an internal sounder that is activated upon detection of any of the channels (with the exception of 'EPS supplying load').

The sounder can be muted by pressing the integral alarm mute  button. Once muted, any subsequent alarm condition will retrigger the sounder.

Pressing the lamp test  button will illuminate all LEDs to prove their operational state.

4.1.1 FRONT PANEL LAYOUT



Panel cutout : 154mm x 98mm (6.1" x 3.9")

4.1.2 REAR PANEL LAYOUT



4.2 TERMINAL DESCRIPTION

4.2.1 CONNECTOR 1


PIN No	DESCRIPTION	CABLE SIZE	NOTES
A	0V	0.5mm ²	Thinner cable will reduce the maximum allowable cable length
B	A	0.5mm ²	
C	B	0.5mm ²	
D	+12V	0.5mm ²	

! CAUTION!: Connector 1 is only intended for connection to the DSE 549 annunciator. Connection to any other device may cause damage and will invalidate the warranty.

4.2.2 TYPICAL CONNECTION SCHEMATICS :

Configuration / monitoring PC

549 Remote Annunciator




NOTE:- Previously, the 53xx expansion port was used solely for output expansion. For this reason, modules manufactured prior to the release of the P130 input expansion module may be marked as : **157/548 ✓**. These 'early' modules are not compatible with the P130 input expansion module.

4.3 549 REMOTE ANNUNCIATOR SPECIFICATION

DC Supply	8.0 to 35 V Continuous.
Cranking Dropouts	Able to survive 0 V for 50 mS, providing supply was at least 10 V before dropout and supply recovers to 5V
Max. Operating Current	150mA at 12V. 81mA at 24V. This maximum current includes the P130, which provides power to the P549.
Dimensions	171mm x 115mm x 49mm (6¾" x 4½" x 2")
Operating Temperature Range	-30°C to +70°C
IP Rating of P549 fascia	IP55 when fitted into control panel with supplied gasket
Connector 1 max cable length to P130 input expansion module	<ul style="list-style-type: none"> 1000m with cable of 0.5mm² cross section 500m with cable of 0.2mm² cross section (typical 4 core burglar alarm/telephone wire)

4.4 TYPICAL WIRING DIAGRAM



5 TYPICAL WIRING DIAGRAM OF P130 WITH P549

