# **SDMO**°





#### DESCRIPTIVE

- Mechanic governor
- Mechanically welded chassis with antivibration suspension
- Main line circuit breaker

Radiator for wiring temperature of 48/50°C max with mechanical fan

- Protective grille for fan and rotating parts (CE option)
- 9 dB(A) silencer supplied separately
- Charger DC starting battery with electrolyte
- 12 V charge alternator and starter
- Delivered with oil and coolant -30°C
- Manual for use and installation

# J60UM

Engine ref.	4045TF120
Alternator ref.	AT00911T
Performance class	G3
GENERAL CHARACTERISTICS Frequency (Hz)	60

Voltage (V)	240 single phase
Standard Control Panel	APM303
Optional control panel	TELYS

POWER						
Voltage	ESP		PRP		Standby Amna	
	kWe	kVA	kWe	kVA	Standby Amps	
240 MONO_BI	60	60	55	55	250	

DIMENSIONS COMPACT VERSION	
Length (mm)	1870
Width (mm)	994
Height (mm)	1360
Dry weight (kg)	1187
Tank capacity (L)	190

DIMENSIONS SOUNDPROOFED	VERSION
Commercial reference of the enclosure	M129
Length (mm)	2554
Width (mm)	1150
Height (mm)	1680
Dry weight (kg)	1577
Tank capacity (L)	190
Acoustic pressure level @1m in dB(A)	77
Sound power level guaranteed (Lwa)	0
Acoustic pressure level @7m in dB(A)	67

#### **POWER DEFINITION**

PRP : Prime Power is available for an unlimited number of annual operating hours in variable load applications, in accordance with ISO 8528-1. ESP : The standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO 8528-1. Overload is not allowed.

#### TERMS OF USE

According to the standard, the nominal power assigned by the genset is given for 25°C Air Intlet Temperature, of a barometric pressure of 100 kPA (100 m A.S.L), and 30 % relative humidity. For particular conditions in your installation, refer to the derating table.

#### ASSOCIATED UNCERTAINLY

For the generating sets used indoor, where the acoustic pressure levels depends on the installation conditions, it is not possible to specify the ambient noise level in the exploitation and maintenance instructions. You will also find in our exploitation and maintenance instructions a warning concerning the air noise dangers and the need to implement appropriated preventive measures.

3/27/2015

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.



# J60UM

## **ENGINE CHARACTERISTICS**

#### **GENERAL ENGINE DATA**

Engine model	JOHN DEERE
Engine ref.	4045TF120
Air inlet	Turbo
Cylinders arrangement	L
Number of cylinders	4
Displacement (C.I.)	4.48
Air coolant	
Bore (mm) x Stroke (mm)	106 x 127
Compression ratio	17 : 1
Speed (RPM)	1800
Pistons speed (m/s)	7.62
Maximum stand-by power at rated RPM (kW)	80
Frequency regulation (%)	+/- 2.5%
BMEP (bar)	10.70
Governor type	Mechanical

#### **COOLING SYSTEM**

Radiator & Engine capacity (L)	23.60
Max water temperature (°C)	105
Outlet water temperature (°C)	93
Fan power (kW)	2.50
Fan air flow w/o restriction (m3/s)	3
Available restriction on air flow (mm Water Column)	20
Type of coolant	Glycol-Ethylene
Thermostat (°C)	82-94

#### EMISSIONS

Emission PM (g/kWh) Emission CO (g/kW.h) Emission HCNOx (g/kWh) Emission HC (g/kW.h)

EXHAUST	
Exhaust gas temperature (°C)	520
Exhaust gas flow (L/s)	220
Max. exhaust back pressure (mm EC)	750
FUEL	
Fuel consumption 110% load (L/hr)	20.50
Fuel consumption 100% load (L/hr)	19
Fuel consumption 75% (L/h)	14.50
Fuel consumption 50% (L/h)	10.50
Maximum fuel pump flow (L/h)	112
OIL	
Oil capacity (L)	13.50
Min. oil pressure (bar)	1
Max. oil pressure (bar)	5
Oil consumption 100% load (L/h)	0.02
Carter oil capacity (L)	12.50

HEAT BALANCE	
Heat rejection to exhaust (kW)	63
Radiated heat to ambiant (kW)	9
Haet rejection to coolant (kW)	39

AIR INTAKE	
Max. intake restriction (mm EC)	625
Intake air flow (L/s)	88

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

3/27/2015



# J60UM

## **ALTERNATOR CHARACTERISTICS**

#### **GENERAL DATA**

Alternator ref.	AT00911T
Number of Phase	Single phase
Power factor (Cos Phi)	1
Altitude (m)	0 to 1000
Overspeed (rpm)	2250
Number of pole	4
Capacity for maintaining short circuit at 3 In for 10 s	No
Insulation class	Н
T° class, continuous 40°C	H / 125°K
T° class, standby 27°C	H / 163°K
AVR Regulation	Yes
Total Harmonic Distortion in no-load DHT (%)	<2
Total Harmonic Distortion, on load DHT (%)	<5
Wave form : NEMA=TIF	<50
Wave form : CEI=FHT	
Number of bearing	1
Coupling	Direct
Voltage regulation at established rating (+/-%)	
Recovery time (Delta U = 20% transcient) (ms)	500
Indication of protection	IP 23
Technology	Without collar or brush

Standby Rating 27°C (kVA)7Efficiencies 100% of load (%)7Air flow (m3/s)6Short circuit ratio (Kcc)6Direct axis synchro reactance unsaturated (Xd) (%)2Quadra axis synchro reactance unsaturated (Xd) (%)2Open circuit time constant (T'do) (ms)2Direct axis transcient reactance saturated (X'd) (%)1Direct axis transcient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Quadra axis subtranscient reactance saturated (X''d) (%)1Quadra axis subtranscient (T''q) (ms)1Quadra axis subtranscient (T''q) (ms)1Zero sequence reactance unsaturated (Xo) (%)1No load excitation current (io) (A)1Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	
Efficiencies 100% of load (%)SAir flow (m3/s)CShort circuit ratio (Kcc)CDirect axis synchro reactance unsaturated (Xd) (%)2Quadra axis synchro reactance unsaturated (Xq) (%)1Open circuit time constant (T'do) (ms)2Direct axis transcient reactance saturated (X'd) (%)1Short circuit transcient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Direct axis subtranscient reactance saturated (X'd) (%)1Quadra axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'd) (ms)1Quadra exis subtranscient reactance saturated (Xo) (%)1Negative sequence reactance unsaturated (Xo) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	65
Air flow (m3/s)CShort circuit ratio (Kcc)CDirect axis synchro reactance unsaturated (Xd) (%)2Quadra axis synchro reactance unsaturated (Xq) (%)1Open circuit time constant (T'do) (ms)2Direct axis transcient reactance saturated (X'd) (%)1Short circuit transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'd) (ms)1Quadra axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'd) (ms)1Quadra axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'd) (ms)1Quadra axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'q) (ms)1Zero sequence reactance unsaturated (Xo) (%)1Negative sequence reactance saturated (Xo) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	72
Short circuit ratio (Kcc)CDirect axis synchro reactance unsaturated (Xd) (%)2Quadra axis synchro reactance unsaturated (Xq) (%)1Open circuit time constant (T'do) (ms)2Direct axis transcient reactance saturated (X'd) (%)1Short circuit transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X'd) (%)1Short circuit transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X'd) (%)1Subtranscient time constant (T'd) (ms)1Quadra axis subtranscient reactance saturated (X''q) (%)1Subtranscient time constant (T''q) (ms)1Zero sequence reactance unsaturated (Xo) (%)1Negative sequence reactance saturated (Xo) (%)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	94.60
Direct axis synchro reactance unsaturated (Xd) (%)Quadra axis synchro reactance unsaturated (Xq) (%)Open circuit time constant (T'do) (ms)Direct axis transcient reactance saturated (X'd) (%)Short circuit transcient time constant (T'd) (ms)Direct axis subtranscient reactance saturated (X'd) (%)Subtranscient time constant (T'd) (ms)Quadra axis subtranscient reactance saturated (X'd) (%)Subtranscient time constant (T'd) (ms)Quadra axis subtranscient reactance saturated (X''q) (%)Subtranscient time constant (T''q) (ms)Zero sequence reactance unsaturated (Xo) (%)Negative sequence reactance saturated (Xo) (%)Armature time constant (Ta) (ms)No load excitation current (io) (A)Full load excitation voltage (uc) (V)Engine start (Delta U = 20% perm. or 50% trans.)(kVA)Transcient dip (4/4 load) - PF : 0,8 AR (%)	0.30
Quadra axis synchro reactance unsaturated (Xq) (%)Open circuit time constant (T'do) (ms)Direct axis transcient reactance saturated (X'd) (%)Short circuit transcient time constant (T'd) (ms)Direct axis subtranscient reactance saturated (X'd) (%)Subtranscient time constant (T'd) (ms)Quadra axis subtranscient reactance saturated (X'd) (%)Subtranscient time constant (T"d) (ms)Quadra axis subtranscient reactance saturated (X"q)(%)Subtranscient time constant (T"q) (ms)Zero sequence reactance unsaturated (Xo) (%)Negative sequence reactance saturated (Xo) (%)Armature time constant (Ta) (ms)No load excitation current (io) (A)Full load excitation current (ic) (A)Full load excitation voltage (uc) (V)Engine start (Delta U = 20% perm. or 50% trans.)(kVA)Transcient dip (4/4 load) - PF : 0,8 AR (%)	0.52
Open circuit time constant (T'do) (ms)2Direct axis transcient reactance saturated (X'd) (%)1Short circuit transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X'd)8(%)1Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X"d)1(%)1Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X"q)1(%)1Subtranscient time constant (T"q) (ms)1Zero sequence reactance unsaturated (Xo) (%)1Negative sequence reactance saturated (Xo) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	299
Direct axis transcient reactance saturated (X'd) (%)Direct axis transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X''d)8(%)1Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X''q)1(%)1Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X''q)1(%)1Subtranscient time constant (T"q) (ms)1Zero sequence reactance unsaturated (Xo) (%)1Negative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	179
Short circuit transcient time constant (T'd) (ms)1Direct axis subtranscient reactance saturated (X"d)8(%)1Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X"q)1(%)1Subtranscient time constant (T"q) (ms)1Zero sequence reactance unsaturated (Xo) (%)0Negative sequence reactance saturated (Xo) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)1Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	2211
Direct axis subtranscient reactance saturated (X"d) (%)8Subtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X"q) (%)1Subtranscient time constant (T"q) (ms)1Zero sequence reactance unsaturated (Xo) (%)0Negative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)2Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.) (kVA)3Transcient dip (4/4 load) - PF : 0,8 AR (%)1	13.50
(%)CSubtranscient time constant (T"d) (ms)1Quadra axis subtranscient reactance saturated (X"q)1(%)Subtranscient time constant (T"q) (ms)Zero sequence reactance unsaturated (Xo) (%)CNegative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)CFull load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)Transcient dip (4/4 load) - PF : 0,8 AR (%)1	100
Quadra axis subtranscient reactance saturated (X"q) (%)1Subtranscient time constant (T"q) (ms)Zero sequence reactance unsaturated (Xo) (%)0Negative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)0Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.) (kVA)3Transcient dip (4/4 load) - PF : 0,8 AR (%)1	8.10
(%)Subtranscient time constant (T"q) (ms)Zero sequence reactance unsaturated (Xo) (%)Negative sequence reactance saturated (X2) (%)Armature time constant (Ta) (ms)No load excitation current (io) (A)Full load excitation current (ic) (A)Full load excitation voltage (uc) (V)Engine start (Delta U = 20% perm. or 50% trans.)(kVA)Transcient dip (4/4 load) - PF : 0,8 AR (%)	10
Zero sequence reactance unsaturated (Xo) (%)CNegative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)CFull load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)1Transcient dip (4/4 load) - PF : 0,8 AR (%)1	16.70
Negative sequence reactance saturated (X2) (%)1Armature time constant (Ta) (ms)1No load excitation current (io) (A)1Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)3Transcient dip (4/4 load) - PF : 0,8 AR (%)1	
Armature time constant (Ta) (ms)1No load excitation current (io) (A)0Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)7Transcient dip (4/4 load) - PF : 0,8 AR (%)1	0.41
No load excitation current (io) (A)CFull load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.) (kVA)3Transcient dip (4/4 load) - PF : 0,8 AR (%)1	12.44
Full load excitation current (ic) (A)2Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.)3(kVA)7Transcient dip (4/4 load) - PF : 0,8 AR (%)1	15
Full load excitation voltage (uc) (V)2Engine start (Delta U = 20% perm. or 50% trans.) (kVA)3Transcient dip (4/4 load) - PF : 0,8 AR (%)1	0.71
Engine start (Delta U = 20% perm. or 50% trans.) (kVA) Transcient dip (4/4 load) - PF : 0,8 AR (%)	2.26
(kVA) Transcient dip (4/4 load) - PF : 0,8 AR (%)	28
	339
	12.70
No load losses (W) 3	3410
Heat rejection (W) 8	8187

Unbalanced load acceptance ratio (%)

### DIMENSIONS

Containment DW	
Commercial reference of the enclosure	M129 DW
Length (mm)	2602
Width (mm)	1150
Height (mm)	1900
Dry weight (kg)	1996
Tank capacity (L)	505
Acoustic pressure level @1m in dB(A)	77
Sound power level guaranteed (Lwa)	0
Acoustic pressure level @7m in dB(A)	67

3/27/2015 This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.



## J60UM

## **CONTROL PANEL**

#### APM303, comprehensive and simple



The APM303 is a versatile unit which can be operated in manual or automatic mode. Equipped with an LCD screen, the user-friendly APM303 offers high-quality basic functions to guarantee simple, reliable operation and supervision of your generating set. It offers the following features: Measurements:

phase-to-neutral and phase-to-phase voltages, active power currents, effective power, power factors, Kw/h energy meter Fuel, oil pressure and coolant temperature levels Supervision:

Modbus RTU communication on RS485 Reports: 2 configurable reports Safety features: Overspeed, oil pressure Coolant temperatures Minimum and maximum voltage Minimum and maximum frequency Maximum current Maximum active power Phase sequence Traceability: Stack of 12 stored events For further information, please refer to the data sheet for the APM303.

#### TELYS, ergonomic and user-friendly



The highly versatile TELYS control unit is complex yet accessible, thanks to the particular attention paid to optimising its ergonomics and ease of use. With its large display screen, buttons and scroll wheel, it places the accent on simplicity and communication.

The TELYS offers the following functions:

Electrical measurements: voltmeter, frequency meter, ammeter.

Engine parameters: working hours counter, oil pressure, coolant temperature, fuel level, engine speed, battery voltage.

Alarms and faults: oil pressure, coolant temperature, failure to start, overspeed, alternator min./max., battery voltage min./max., emergency stop, fuel level.

Ergonomics: wheel for navigating around the various menus.

Communication: remote control and operation software, USB connections, PC connection.

For more information on the product and its options, please refer to the sales documentation.

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

3/27/2015

3/27/2015 This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.